

General product information page 1/2



BATTERY LIFE

Candle:	up to 100 hours
Ambient:	up to 80 hours
Work:	up to 65 hours

CHARGING

Charging in two ways possible:	with a power cable (USB-C to USB-A) and wirelessly.
Charging time to full power with USB cable:	up to 4 hours, depending on what adaptor is used.
Charging time to full power wirelessly:	up to 6 hours with 10W wireless charger.

Any Qi certified wireless charger is suitable to charge a Humble ONE light.

BATTERY LEVEL

LED indicator lights on the base of the light will tell you the battery level.	
LED 1 flashing:	battery level < 5 % and in need of a charge.
1 LED on:	battery level is 6%–33%.
2 LED's on:	battery level is 34%–66%.
3 LED's on:	battery level is 67% – 100%.

To show you the battery level, the LED's will light up for 10 seconds after any brightness adjustment or after pressing the battery indicator button on the remote.

BULB

The base is designed for use with replaceable low-voltage E27 bulbs.
Note: The Humble lights will ONLY support low-voltage bulbs. The bulbs are separately available on our website: www.humblelights.com.

MATERIALS

Base:	aluminium
Cover:	iron with painted finish or hydrodip print
Bulb:	glass
Seals:	silicon
Cable:	USB type-A to USB type-C (certified)

TECHNICAL SPECS

Light source:	E27 low-voltage bulb
Power:	1W, 5V
Kelvin:	2200k
Dimmable:	yes, 3 levels
Lumen:	Candle 8 lm Ambient 16 lm Work 43 lm
Battery capacity:	4000 mAh
Charging cable:	USB-C to USB-A
Control:	Toggle switch on bottom of base

CONTACT

Humble by Spacesplus B.V.
Herengracht 189a
1016 BE, Amsterdam
The Netherlands

e	info@humblelights.com
w	humblelights.com
i	@humble.lights

General product information page 2/2

humble one



Total weight: 0,375 kg

