



PA3M

Clamp splitters of the PAM series in the TV and Satellite band (**5-2400MHz**).

Thanks to the **exclusive fixing spring clamp**, the central connector remains integral with the rest of the mechanics, facilitating the fixing of the cable.

The new mechanics with **very small dimensions** and the clamp solution, without F connector, significantly reduce the installation footprint.

The excellent shielding guarantees the protection of the signal from LTE disturbances in the air.

ITEM		PA3M
Code		287457
Outputs		3
Insertion loss (dB)	RC 5-40 MHz	6,6
	TV 47-862 MHz	7,2
	SAT 950-1750 MHz	8,1
	SAT 1750-2150 MHz	8,5
	SAT 2150-2400 MHz	10,5
Outputs Isolation (dB)	RC 5-40 MHz	21
	TV 47-862 MHz	21
	SAT 950-1750 MHz	21
	SAT 1750-2150 MHz	21
	SAT 2150-2400 MHz	20