



ANT1200A

FM band antenna with connector for the reception of **radio signals**.

- FM and DAB band antennas
- with F connector
- With different types of designs for collective and centralized reception of radio signals

ANT1200A		
Code		213001
Elements	no.	1
Band		FM
Channel		
Bandwidth	MHz	87.5-108
Gain	dBi	2.1
Front/Back ratio	dB	Omni
Return loss	dB	-16
Beam width (-3dB)	°	360
Wind load at 120km/h (720N/m ²)	kg (N)	3 (29.43)
Connector	Type	F
Impedance	Ω	75
Max mast (Ø)	mm	60
Dimensions (L x H)	cm	96 x 77
Quantity Master box	pcs	10
Unit weight	kg	0.9
Total weight	kg	10.6

Accessories

Horizontal polarization	Included
Horizontal polarization Tilt adjustment	N/A
Vertical polarization	
Vertical polarization Tilt adjustment	
Auxiliary boom	N/A