

DE2-18



F connector **vertical taps** for TV and Satellite band (**5-2400MHz**)

| ITEM | | DE2-18 |
|------------------------|-------------------|--------|
| Code | | 280716 |
| Taps | | 2 |
| Insertion loss (dB) | RC 5-40 MHz | 1,2 |
| | TV 47-862 MHz | 1,2 |
| | SAT 950-1750 MHz | 1,5 |
| | SAT 1750-2150 MHz | 1,8 |
| | SAT 2150-2400 MHz | 2 |
| Tap loss (dB) | RC 5-40 MHz | 18 |
| | TV 47-862 MHz | 18 |
| | SAT 950-1750 MHz | 18 |
| | SAT 1750-2150 MHz | 18 |
| | SAT 2150-2400 MHz | 19 |
| Outputs Isolation (dB) | RC 5-40 MHz | 45 |
| | TV 47-862 MHz | 33 |
| | SAT 950-1750 MHz | 27 |
| | SAT 1750-2150 MHz | 27 |
| | SAT 2150-2400 MHz | 25 |